

Габаритные, установочные и присоединительные размеры электродвигателей пониженной высоты
(модификаций 4АМН, 5АН, 5АМН, 5АНМ)

Габарит ЭД	Число полюсов	Габаритные размеры				Установочные и присоединительные размеры, мм															
		l30	l33	h31	d30	b10	l10	l31	d1	d2	l1	l2	b1	b2	h5	h6	h1	h2	h	h10	d10
		L	LC	HD	AC	A	B	C	D	DA	E	EA	F	FA	GA	GC	GD	GF	H	HA	K
4АМН 160S	2	558	675	430	340	254	178	108	42	42	110	110	12	12	45	45	8	8	160	18	15
	4	558	675	430	340	254	178	108	48	42	110	110	12	12	51,5	45	9	8	160	18	15
4АМН 160M	2	601	718	430	340	254	210	108	42	42	110	110	14	12	45	45	8	8	160	18	15
	4	601	718	430	340	254	210	108	48	42	110	110	14	12	51,5	45	9	8	160	18	15
4АМН 180S	2	580	695	445	378	279	203	121	48	48	110	110	14	14	51,5	51,5	9	9	180	20	15
	4, 6, 8	580	695	445	378	279	203	121	55	48	110	110	16	14	59	51,5	10	9	180	20	15
4АМН 180M	2	620	735	445	378	279	241	121	48	48	110	110	14	14	51,5	51,5	9	9	180	20	15
	4, 6, 8	620	735	445	378	279	241	121	55	48	110	110	16	14	59	51,5	10	9	180	20	15
5АН 200M	2	720	835	490	410	318	267	133	55	55	110	110	16	16	59	59	10	10	200	25	19
	4, 6, 8	750	865	490	410	318	267	133	60	55	140	110	18	16	64	59	11	10	200	25	19
5АН 200L	2	750	865	490	410	318	305	133	55	55	110	110	16	16	59	59	10	10	200	25	19
	4, 6, 8	780	895	490	410	318	305	133	60	55	140	110	18	16	64	59	11	10	200	25	19
5АН 225M	2	755	-	575	485	356	311	149	55	-	110	-	16	-	59	-	10	-	225	28	19
	4, 6, 8	785	-	575	485	356	311	149	65	-	140	-	18	-	69	-	11	-	225	28	19
5АМН 250S	2	935	1085	630	545	406	311	168	65	65	140	140	18	18	69	69	11	11	250	30	24
	4, 6, 8	935	1085	630	545	406	311	168	75	70	140	140	20	20	79,5	74,5	12	12	250	30	24
5АМН 250M	2	965	1115	630	545	406	349	168	65	65	140	140	18	18	69	69	11	11	250	30	24
	4, 6	965	1115	630	545	406	349	168	75	70	140	140	20	20	79,5	74,5	12	12	250	30	24
	8	935	1085	630	545	406	349	168	75	70	140	140	20	20	79,5	74,5	12	12	250	30	24
5АМН 280S	4, 6, 8	1110	1260	710	620	457	368	190	80	65	170	140	22	18	85	69	14	11	280	30	24
5АМН 280M	2	1080	1230	710	620	457	419	190	70	60	140	140	20	18	74,5	64	12	11	280	30	24

	4, 6	1180	1330	710	620	457	419	190	80	65	170	140	22	18	85	69	14	11	280	30	24
	8	1110	1260	710	620	457	419	190	80	65	170	140	22	18	85	69	14	11	280	30	24
5AH 280A	2	975	-	745	665	457	368, 419*	190	70	-	140	-	20	-	74,5	-	12	-	280	25	24
	4, 6, 8, 10	1005	-	745	665	457		190	80	-	170	-	22	-	85	-	14	-	280	25	24
5AH 280B	2	1035	-	745	665	457		190	70	-	140	-	20	-	74,5	-	12	-	280	25	24
	4, 6, 8, 10	1005	-	745	665	457		190	80	-	170	-	22	-	85	-	14	-	280	25	24
5AMH 315S	2	1160	1310	815	680	508	406	216	75	65	140	140	20	18	79,5	69	12	11	315	40	28
	4	1290	1440	815	680	508	406	216	90	65	170	140	25	18	95	69	14	11	315	40	28
	6, 8	1190	1340	815	680	508	406	216	90	65	170	140	25	18	95	69	14	11	315	40	28
5AMH 315M	2	1260	1410	815	680	508	457	216	75	65	140	140	20	18	79,5	69	12	11	315	40	28
	4	1290	1440	815	680	508	457	216	90	65	170	140	25	18	95	69	14	11	315	40	28
	6, 8	1190	1340	815	680	508	457	216	90	65	170	140	25	18	95	69	14	11	315	40	28
5AHM 315MA,MB	2	1020	-	1020	730	508	457	216	75	-	140	-	20	-	79,5	-	12	-	315	40	28
	6, 8, 10	1050	-	1020	730	508	457	216	90	-	170	-	25	-	95	-	14	-	315	40	28
5AH 315A	2	1010	-	816	740	508	406, 457*	216	75	-	140	-	20	-	79,5	-	12	-	315	30	28
5AH 315A,B	4, 6, 8, 10	1040	-	816	740	508		216	90	-	170	-	25	-	95	-	14	-	315	30	28
5AH 355A,B	2	1135	-	900	820	610	500, 560*	254	85	-	170	-	22	-	90	-	14	-	355	35	28
	4, 6, 8, 10	1175	-	900	820	610		254	100	-	210	-	28	-	106	-	16	-	355	35	28

* электродвигатель изготовлен на два размера (по 3 отверстия в каждой лапе)